

UNITIMER programmer

PRECISION & MULTI-PURPOSE

UNITIMER is the ideal electronic programmer for your network, or photovoltaic installations or 12 or 24 V network.

UNITIMER turns your 12V electrical devices automatically and accurately on and off. Its applications are many: lighting, watering, fountains, preheating, light display, alarm, video surveillance...

This way UNITIMER saves your energy for more amplitude of operation.

UNITIMER has many advantages:

- more than 17 different ignition and extinction programs available (weekend, everyday choice, multi-day ...),
- LCD display with transparent protective cover,
- NO or NC connection (NO = normally opened, NC = normally closed) for more security depending on your uses,
- built-in lithium battery to preserve your programs in case of power failure.



+ UNITECK



Up to 17 programs



Low self-consumption



Back up on Lithium battery



Broad range of operating temperature (-10/+40°C)



Quality guaranteed by Uniteck
Made in P.R.C.



**UNITIMER
16.12**

Ref 1221



**UNITIMER
16.24**

Ref 1382

System

Input voltage	12 V	24 V
Accepted voltage range	10-15 V	20-30 V
Max. current	16 A	
Self-consumption:		
-Relay ON position	>0,6 W (50mA)	>0,6 W (25mA)
-Relay OFF position	>0,08 W (8mA)	>0,08 W (4mA)
Protection class	IP44	
Operating temperature	-10°C à + 40°C	

Programmer

Number of programs	17 ignitions/extinctions	
Inter-program interval	1 min	
Backup battery	Battery CR2032 (3 years)	

Mechanical characteristics

Dimensions (W x H x D)	86,5x36x65,5 mm	
Weight	110 g	

Warranty

Period	2 years	2 years
--------	---------	---------